

## GF-07 enhanced magnetic locator

### The instructions

Warm prompt: we are in pursuit of quality, practical, sound is clearer, more accurate positioning, standby time is longer, not blindly pursue low-end KengMeng consumers inferior products. Enhanced alarm locator is a base station positioning in a best cost-effective, higher requirements for high-end customers, let you really buy the rest assured, with enjoyable. Not some fake products; Through low inferior chip, the cost is low, quality is not guaranteed.

#### Product advantage:

1. is the only similar products of all mobile phones on the map to view the query to the location and computer platform position trajectory, also can be directly reply messages in Chinese position.
2. In the first base station positioning on the basis of the original joined Google maps positioning, greatly reduces the error range of the product.
3. Due to the joined Google positioning mode, the product positioning function now support abroad.
4. If we can call 10086 opened around listening to sound more friendship number per month, it's only a number five yuan a month to check how long don't money.
5. This product does not need to cost platform, life-long free of charge. Just send a message to the alarm locator, can respond to the following address information in Chinese and Google maps connection, simple operation, one pace reaches the designated position.
6. This product built-in powerful magnet adsorption function, need not you worry again put problem, as long as there is metal, you can directly put up, the magnet will automatically adsorption, more convenient installation you put the position



Regardless of alarm locator on the cart, children bag, the old man's pocket, valuables bag, can through the mobile phone to send SMS alarm locator, query alarm locator location, convenient you to monitor all the way, to master the location of the object in real time.

#### Method of use:

1. Preparation: a SIM phone card and mini memory card,
2. Boot: open the card cover according to the directions insert SIM card, mini memory card is inserted in, products will be automatically switched on the red light shine out 4 times, 30 seconds to enter standby state.
3. The indicator light: light is normally on four boot, low battery indicator light flash
4. binding master number: Using a mobile phone text 000 sent to alarm the locator number, later the machine reply to phone a message; The set, Binding

6. This product is the only market with the function of charge automatically boot, connect the power supply, when the alarm locator electricity used up and products after shutdown, call the product will be automatically switched on and continue to recharge, warning, charging must insert SIM card
7. Our website [HTTP://gpsui.net](http://gpsui.net)

#### + master number

5. Separate recordings; Using a mobile phone text 555 sent to alarm the locator number, later the machine reply to phone a message; 【 Snd, recording started 】
6. The voice control callback; Using a mobile phone text 666 sent to alarm the locator number, later the machine reply to phone a message; 【 DT, has been successfully set sound monitor, alarm telephone callback 】  
When the sound of the alarm locator around more than 40 db, alarm locator will automatically call set phone number in advance.
7. GPRS location query: edit mobile phone text messages sent to alarm the locator number 777, later reply phone a native Chinese geographical location and Google maps link, location map will be shown after the mobile phone to open the links and text address, make a more accurate location.
- Around 8. Product voice query: direct dialing alarm locator card number, after a few seconds to can hear the sound of the alarm locator around (in the query will not make any sound and light alarm locator itself)
9. The location path query: Use their phones to edit text messages sent to alarm the locator number 102, reply later native mobile a/account, password, website [HTTP://gpsui.net](http://gpsui.net)
10. Delete the content of the memory CARDS; Use their phones to edit text messages sent to alarm the locator number 445, native reply later phone a 【 】 TF, clean up the success, the current can have capacity
11. The state of the host; Using a mobile phone text 888 sent to alarm the locator number, later the machine reply to phone a message; 【 host all the features on or off battery capacity binding number, signal strength, frequency startup, GPRS TF card capacity etc.】
12. Restart the host; Using a mobile phone text 999 sent to alarm the locator number, such as 1 minute recovery success.
13. Shut down, the information above are remaining power according to stop function; Use their phones to edit text messages sent to alarm the locator

number 444, a native reply later mobile phones and "Reset, all tasks have been cancelled"

14. Electricity query: located in every time you reply,  
(this product can also be an external smoke alarm door magnetic shoe bag need to increase the functions such as water or customized products and the suggestion, please contact the dealer)

1. Appearance size: 3.5 cm \* 2.0 cm \* 1.4 cm (L \* W \* H)
  2. Charging input InputAC110-220 v50/60 hz
  3. The charging output: OutputDC5.0 V 300-500 ma
  4. The machine battery: 3.7 V 400 mah Li - ion
  5. Standby time: 12 days. Working time 4 to 6 days
  6. The expansion card, Mini TF card
  7. The video video: 320 \* 240
  8. The photo size: 640 \* 480
  9. Talk: 150-180 minutes
  10. Format: GSM/GPRS
  11. Storage temperature: - 40 ° C to + 85 ° C
  12. Working temperature - 20 ° C to + 55 ° C
  13. Humidity range 5% - 95% non - condensing
  14. GPRS: Upload60, TCP/IP
  15. working voltage: 3.4-4.2 V DC
  - 16 standby current: material 2.5 mA
  17. open the acoustic current: material 30 ma
  18. call: current material 150 ma
  19. GSM positioning time: 25 seconds
- Basic parameters: spectrum GSM850/900/1800/1900 MHZ  
Supported countries: China Britain France Germany Netherlands Italy Spain Brazil, Portugal, Denmark Russia Poland Turkey Hungary Thailand Indonesia Malaysia Vietnam myanmar Pakistan, Iraq, Saudi Arabia, Greece the kazakhstan Mongolia dubai, etc...

## GP-07 加强版磁铁定位器

### 说明书

温馨提示:我们追求的是质量,实用性,声音更清晰,定位更准确,待机时间更长,并非一味追求低端劣质产品坑蒙广大消费者,加强版报警定位器属基站定位比最好的一款,针对要求较高的高端客户,让你真正买的放心,用的舒心,并非市场一些山寨产品;采用低价劣质芯片,成本低廉,质量得不到保障。

产品优势:

1.是所有同类产品中唯一即可用手机在地图上查看到位置和电脑平台查询位置轨迹,也可直接短信中文回复位置的。

2.先在基站定位原有的基础上加入了谷歌地图定位,让产品的误差距离大大缩短。

3.由于加入了谷歌定位模式,产品现支持国外定位跟踪功能。


4.如查听周围声音比较多可打10086开通友情号码月租,一个号只需要5元一月查听多久都不要钱了。

5.本产品不需要平台费用,终身免费使用。只需发一个短信到报警定位器上,即可回复如下中文地址信息和谷歌地图连接,全程手机简单操作,一步到位。

6.本产品内置两块强力磁铁吸附功能,无需您再烦恼摆放的问题,只要有金属的地方,您都可以直接摆放上去,磁铁会自动吸附上去,更方便你安装摆放位置

6.本产品是市场唯一一款带充电自动开机功能,也就是连接电源,当报警定位器电用尽,产品关机后,来电产品将自动开机并继续充电。**警告、充电必须插入SIM卡**

7. 登陆网站 <http://gpsui.net>



不管报警定位器放在车上,小书包里,老人口袋里,贵重物品包包,都可以通过手机给报警定位器发送手机短信指令,查询报警定位器所在位置,方便您全程监控,实时掌握目标的位置。

使用方法:

1. 准备: 一张SIM手机卡和迷你内存卡,

2. 开机: 打开卡盖按指示方向插入SIM卡,在插入迷你内存卡,产品将自动开机红灯闪亮4次熄灭,30秒后进入正常待机状态。【注意如果不读内存卡重新插上】

3.指示灯: 开机指示灯常亮4次熄灭,低电量指示灯快闪

4.绑定主控号码: 用手机编辑短信000发送给报警定位器号码,稍后本机回复手机一条短信: Set:绑定+主控号码

5.单独录音: 用手机编辑短信555发送给报警定位器号码,稍后本机回复手机一条短信: 【Snd:录音已开始】

6.声控回拨: 用手机编辑短信666发送给报警定位器号码,稍后本机回复手机一条短信: 【DT:已成功设定声音监控,警报电话回拨】。当报警定位器周围声音大于40分贝的声音,报警定位器将自动呼叫事先设定的手机号码。

7. GPS定位查询: 用手机编辑短信777发送给报警定位器号码,稍后本机回复手机一条中文地理位置和的谷歌地图链接,手机打开这条链接后会呈现位置地图和文字地址说明,使位置更加准确。

8.产品周围声音查询: 直接拨打报警定位器中卡的号码,几秒钟打通后就可听到报警定位器周围的声音(查询中报警定位器本身不会发出任何声音和亮光)

9.定位轨迹查询: 用手机编辑短信102发送给报警定位器号码,稍后本机回复手机一条【帐号,密码】,登陆网站<http://gpsui.net>

10.定位时时追踪: 在电脑平台操作即可。

11.删除内存卡内容: 用手机编辑短信445发送给报警定位器号码,稍后本机回复手机一条【TF,清理成功,当前可有容量】

12.主机状态: 用手机编辑短信888发送给报警定位器号码,稍后本机回复手机一条短信: 【主机的所有功能开或关 电池容量 绑定号码,信号强弱,开机频率,GPS TF卡容量等】。

13.重启主机: 用手机编辑短信999发送给报警定位器号码,等1分钟恢复成功。

14.关闭、信息上面都有剩余电量的显示停止功能: 用手机编辑短信444发送给报警定位器号码,稍后本机回复手机一条,【Reset:所有任务已取消】

15.电量查询: 在你每次定位回复的信息里都有电量,

【本产品还可以外接 烟感 报警器 门磁 鞋子 书包 水杯 等 需要增加功能或定做产品和建议,请联系经销商】

1.外观尺寸:3.5cm\*2.0cm\*1.4cm(L\*W\*H)

2.充电输入 Input:AC110—220V/50/60Hz

3.充电输出: Output:DC5.0V 300-500mA

4.机器电池: 3.7V 400mAh Li-Ion battery

5.待机时间: 12天。工作时间4-6天

6. 扩展卡: 迷你TF卡

7.连续通话: 150-180分钟

8.网络制式: GSM/GPRS

9.储存温度: -40° C to +85° C

10.工作温度: -20° C to +55° C

11.湿度范围: 5%—95% non-condensing

12.GPRS: Uplink:60,TCPIP

15.工作电压:3.4—4.2V DC

16 待机电流: ≈2.5mA

17.开启声控电流: ≈30mA

18.通话电流: ≈150mA

19.GSM 定位时间: 25秒

基本参数: 频段 GSM850/900/1800/1900MHZ

支持国家: 中国 英国 法国 德国 荷兰 意大利 西班牙 葡萄牙 巴西 丹麦 俄罗斯 波兰 土耳其 匈牙利 泰国 希腊 印尼 马来西亚 越南 缅甸 巴基斯坦 伊拉克 沙特 阿拉伯 美国 哈萨克斯坦 外蒙古 迪拜 等.....

常见问题:

1. 主机无法接通

答: 必须插入SIM手机卡后开机才会启用手机信号,所以您只需要把机器关后重新开机即可。还有就是您的手机卡不在服务器,没有信号。

2. TF 记忆卡无法储存?

答: 先检查一下 TF 记忆卡是否有误问题,如果 TF 卡无问题可以把 TF 记忆卡格式化一下重试。

3. 无法充电?

答: 要充电须插 GSM 卡,如果在没有无法实现充电。

4. 什么是主控手机?

答: 就是你需要用它来监控防盗报警器的手机。

特别警告: 当报警定位器电量不足时(电量在5%以下)请及时进行充电,如电池长期处于亏电状态,必然会造成电池深度放电,影响电池使用性能和寿命,严重者电池充不进电或报废,如报警定位器不使用时,请把电池电量充到60%—80%。断开定位器的电源,在进行存放,长期不用(三个月)请定期把定位器进行补充充电,以保护电池,为了更好的使用本机,请认真阅读并按以上进行操作,谢谢

本产品仅限于个人安全 定位 防丢防盗使用, 严禁非法使用,所产生的 一切法律责任由使用者承担...